

Setting (Android TV OS 14)

Settings are based on the worldwide model. Some settings may differ from EU RED-DA compliant models and China-specific models

Item	Options	Default	Export via USB	Description		
Inputs						
External inputs [HDMI 1 – 4]: You can set whether each input is shown or hidden. Checking "Show this input" will display the corresponding input in the input selection menu.	Manage inputs	HDMI 1	HDMI 1 / Blu-ray / Cable / DVD / Game console / Aux / Custom name	HDMI 1	Allowed	View settings for HDMI 1 input.
		HDMI 2	HDMI 2 / Blu-ray / Cable / DVD / Game console / Aux / Custom name	HDMI 2	Allowed	View settings for HDMI 2 input.
		HDMI 3 (eARC/ARC)	HDMI 3 (eARC/ARC) / Blu-ray / Cable / DVD / Game console / Aux / Custom name	HDMI 3 (eARC/ARC)	Allowed	View settings for HDMI 3 (eARC/ARC) input.
		HDMI 4	HDMI 4 / Blu-ray / Cable / DVD / Game console / Aux / Custom name	HDMI 4	Allowed	View settings for HDMI 4 input.
	BRAVIA Sync settings	BRAVIA Sync control	On / Off	On	Allowed	When set to On, linkage with connected BRAVIA Sync devices is enabled.
		Device auto power off	On / Off	On	Allowed	When you turn off the display, the HDMI device also turns off.
		Auto power on	On / Off	On	Allowed	Sets the display power to [On] when the HDMI connected device is operated.
		BRAVIA Sync device list	—	—	—	List connected Bravia Sync devices.
	HDMI Signal Format / VRR	HDMI 1	Standard format / Enhanced format	Standard format	Allowed	Switches the format for HDMI 1 input.
		HDMI 2	Standard format / Enhanced format	Standard format	Allowed	Switches the format for HDMI 2 input.
		HDMI 3 (eARC/ARC)	Standard format / Enhanced format	Standard format	Allowed	Switches the format for HDMI 3 (eARC/ARC) input.
		HDMI 4	Standard format / Enhanced format	Standard format	—	Switches the format for HDMI 4 input.

Picture & Sound

Content type		Video/Images / Game / PC	Video/Images	Allowed			
Picture	Picture mode	Standard / Professionals / Photo	Standard	Allowed	Picture quality presets based on usage. [Content type] only supports [Video/Images].		
	Reset picture settings	—	—	—	—		
	Brightness	Brightness (SDR)	Min-Max (0~50)	Vary depending on [Content type], [Picture mode]	Allowed	Adjust panel brightness.	
		Contrast (SDR)	Min-Max (0~100)	Vary depending on [Content type], [Picture mode]	Allowed	Adjust area brightness settings.	
		Gamma (SDR)	Min-Max (-3~3)	Vary depending on [Content type], [Picture mode]	Allowed	Mid-tone brightness balance adjustment.	
		HDR tone mapping	—	—	Allowed	Displayed only when "PlayStation 5" is connected, automatic brightness balance adjustment.	
		Black level	Min-Max (0~100)	50	Allowed	Adjust shadow brightness.	
		Black adjust	High / Medium / Low / off	Medium	Allowed	Enhance blacks and auto-adjust black levels.	
		Auto local dimming (SDR)	High / Medium / Low / off	Medium	Allowed	Auto-adjust contrast.	
	Color	Color	Min-Max (0~100)	Vary depending on [Content type], [Picture mode]	Allowed	Adjust color temperature.	
		Hue	Red(50)-G(50)	Vary depending on [Content type], [Picture mode]	Allowed	Shift hue for red, green, and blue.	
		Live Color	High / Medium / Low / off	Off	Allowed	Adjust vividness for each color.	
		Color temperature	Cool / Natural / Warm / Expert 1 / Expert 2	Expert 1	Allowed	Adjust color temperature as the reference standard.	
		Advanced color adjustment	-Individual RGB Gains -40~2 -Individual RGB Bias -20~20 -Reset	Vary depending on [Content type], [Picture mode], and [Color temperature].	Allowed	Individually set RGB gain/bias for selected color temperature.	
		Advanced color temperature: Multi point(10p)	-Color gamma adjustment points 1-10 -Individual RGB Offset -20~20 -Reset	Vary depending on [Content type], [Picture mode], and [Color temperature].	Allowed	Individually set RGB gamma/offset for selected color temperature.	
	Clarity	Sharpness	Min-Max (0~100)	Vary depending on [Content type], [Picture mode], and [Color temperature].	Allowed	Edge enhancement and detail processing.	
		Reality Creation	Auto / Manual / Off Intensity : Min-Max (0~100)	Vary depending on [Content type], [Picture mode], and [Color temperature].	Allowed	Super resolution processing / Noise reduction, image quality improvement.	
		Random noise reduction	High / Medium / Low / off	Medium	Allowed	Improve video quality and noise reduction. Not adjustable depending on [Content type] and [Picture Mode].	
		Digital noise reduction	High / Medium / Low / off	Medium	Allowed	For compressed video with noise. Not adjustable depending on [Contents type] and [Picture Mode].	
		Motion	Custom / Off Smoothness (Film) : Min-Max (0~3) Smoothness (Camera) : Min-Max (0~3) Clearness : Min-Max (0~3)	Custom Smoothness (Film) : Max (3) Smoothness (Camera) : Max (3) Clearness : Min (0)	Allowed	Smooth gradation reproduction. Adjust preferences for smoothness, clarity, and grain.	
	SETTINGS FOR CURRENT INPUT OR APP	Video signal	Color Space	Auto / sRGB/BT.709 / DCI / adobe RGB / BT.2020	Auto	Allowed	Preserve input signal color information.
			HDR mode	Auto / HDR10 / HLG / Off	Auto	Allowed	Set input HDR mode.
	Sound (Built-in speakers)	Surround	Auto / On / Off	Auto	Allowed	Switch gamma processing according to content.	
		Surround effect	Min-Max (0~12)	6	Allowed	Adjust surround sound effect.	
		Voice Zoom	Min-Max (-6~6)	0	Allowed	Adjust voice zoom level.	
		Equalizer	Min-Max (-12~12) Frequency : 125Hz, 250Hz, 500Hz, 1kHz, 2kHz, 4kHz, 8kHz	All 0	Allowed	Adjust sound quality by frequency range.	
Reset		—	—	—	Reset speaker sound quality to default settings.		
VOLUME SETTINGS		Balance	Min-Max (L15~R15)	Center (0)	Allowed	Adjust left/right audio output balance.	
		Advanced auto volume	On / Off	Off	Allowed	Auto volume adjustment.	
		Dolby AC-4 Dialog level	Min-Max (0~6)	3	Allowed	Dolby AC-4 audio support. Adjust human voice level.	
DYNAMIC RANGE SETTINGS		Dynamic range	Standard / Compressed	Compressed	—	Adjust dynamic range.	
		DTS Dynamic range	On / Off	Off	—	Set DTS audio dynamic range.	
GENERAL	Post processing	Standard / Dolby Audio processing / DTS Virtual:X	Standard	—	Select sound processing mode.		
Adjust only for HDMI 1		On / Off	Off	Allowed	Items subject to [Picture] and [Sound] support (HDMI 1 input only, [All] for all inputs/apps).		
Prioritize HDMI signal information		On / Off	On	Allowed	Auto-switch [Viewing Scene] based on content type signal from HDMI-connected device.		
Audio output	Speakers	Built-in speakers / Audio system	Built-in speakers	Allowed	Audio output destination settings.		
	Audio system settings	Audio system prioritization	On / Off	On	Automatically switch audio output to BRAVIA Sync-compatible audio system.		

Setting (Android TV OS 14)

Settings are based on the worldwide model. Some settings may differ from EU RED-DA compliant models and China-specific models

*Shown only when connected	A/V sync	A/V sync	Auto / On / Off	Auto	Allowed	Auto-correct audio output delay.
		Digital audio output	Auto / Prioritize pass through / PCM	Auto	Allowed	Configure digital audio output settings, output level, and digital audio formats such as PCM and passthrough.
		eARC setting	Auto / Off	Auto	Allowed	[Auto] outputs audio to eARC-compatible device connected to HDMI 3 (eARC/ARC) terminal.
	Bluetooth device settings	A/V sync	Auto / On / Off	Auto	Allowed	Adjusts output timing to reduce audio-video sync issues when using Bluetooth audio.
		Bluetooth settings	-	-	Allowed	Enable Bluetooth settings.
	Optical digital audio output settings	Optical digital audio output	On / Off	Off	Allowed	Enable audio output to device connected to optical digital audio output terminal.
Digital audio output		Auto / Prioritize pass through / PCM	Auto	Allowed	Configure optical digital audio output settings, output level, and digital audio formats such as PCM and passthrough.	
Optical digital audio output volume		Min-Max (0~100)	Max (100)	Allowed	Adjust optical digital audio output level.Adjust optical digital audio output level.	
Ambient Optimization Pro	Auto adjust according to ambient light		On / Off	On	Allowed	
	Advanced setting	Auto luminance level	On / Off	On	Allowed	Enable automatic adjustment based on environment.
		Auto tone curve	On / Off	On	Allowed	Adjust brightness balance and auto-tune to [Picture mode].
*Shown only when connected	Auto adjust according to viewing position		On / Off	Off	-	Adjustable when "BRAVIA Cam" is connected.
*Shown only when connected	Advanced settings	-	-	-	-	Adjustable when "BRAVIA Cam" is connected.

Network & Internet

Wi-Fi		On / Off	Off	Allowed	Enable Wi-Fi.	
Available Networks		Available Network lists	-	-	Check list of available networks.	
Add Network			-	-	Manually add a network.	
Scanning always available		On / Off	Off	-	Scan for networks even when Wi-Fi is OFF.	
(ETHERNET)Connected		Disconnected / Connected	Display the status	-	LAN connection status.	
Proxy settings		None / Manual	None	Allowed	Configure proxy settings.	
IP settings		DHCP / Static	-	-	Configure DHCP settings.	
Network status			Display the status	-	Check network connection status.	
Remote device settings	Control remotely	On / Off	On	Allowed	-	
Local network	Server diagnosis	-	-	-	Action	
	DLNA player	On / Off	Off	Allowed	Enables DLNA-compliant devices.	
	IP Control	Authentication	None / Normal / Pre-Shared Key / Normal and Pre-Shared Key	Normal	Allowed	Authentication method setting.
		Pre-Shared Key	Text input	-	Allowed	Pre-Shared Key setting.
		Simple IP control	On / Off	Off	Allowed	Enables Simple IP control.
Control4®	On / Off	Off	Allowed	Enables Control4®		

Privacy

Location	Location status	Use Wi-Fi to estimate location / Off	Off	Allowed	Check Google location status.
	Scanning always available	On / Off	Off	Allowed	Set whether to always scan for location.
Microphone	Microphone access	On / Off	Off	-	Grant access permission to all apps and services.
	App access to microphone	-Individual app permissions: Allowed / Not Allowed	-	-	Select apps to allow from the list. Configurable when connected.
Camera	Camera access	On / Off	Off	-	Grant access permission to all apps and services.
	App access to camera	Individual app permissions: Allowed / Not Allowed	-	-	Select apps to allow from the list. Configurable when connected.
App permissions, Special app access, Security & Restrictions		Refer to Apps	-	-	-

Apps

*Individual app actions	Open	-	-	-	Action.
	Force stop	-	-	-	Action.
	Storage used	-	-	-	Action.
	Clear data	-	-	-	Action.
	Clear cache	-	-	-	Action.
	Clear defaults	-	-	-	Action.
	Notifications	On (Allow) / Off(Not Allowed)	Off	-	External app notification settings.
	Permissions	On (Allow) / Off(Not Allowed)	-	-	List of external input app data sharing permissions.
See all Apps		List of installed and system apps	-	-	Select devices (camera, microphone, etc.) from the list to allow data access.
App permissions			-	-	Individual app permissions: Allowed / Not Allowed
Special app access	Energy optimisation				
	Usage access	On (Allow) / Off(Not Allowed)	-	-	Select apps to allow from the list
	Notification access	On (Allow) / Off(Not Allowed)	-	-	Select apps to allow from the list
	All files access	On (Allow) / Off(Not Allowed)	-	-	Select apps to allow from the list
	Display over other apps	On (Allow) / Off(Not Allowed)	-	-	Select apps to allow from the list
	Media management apps	On (Allow) / Off(Not Allowed)	-	-	Select apps to allow from the list
	Modify system settings	On (Allow) / Off(Not Allowed)	-	-	Select apps to allow from the list
	Alarms & reminders	On (Allow) / Off(Not Allowed)	-	-	Select apps to allow from the list
Turn screen on	On (Allow) / Off(Not Allowed)	-	-	Select apps to allow from the list	
Security & Restrictions	Unknown sources	On (Allow) / Off(Not Allowed)	-	-	Connected apps appear in the list. Allow permission to install them on the monitor.

System

Screen saver	Screen saver	Sleep / BRAVIA Screen Saver / Colors	BRAVIA Screen Save	Allowed	Set screen saver type.
	When to start	5 min / 10 min / 15 min / 30 min / 1 h / 2 h	15 min	Allowed	Set time until screen saver starts.
	Start now	-	-	Allowed	-

Setting (Android TV OS 14)

Settings are based on the worldwide model. Some settings may differ from EU RED-DA compliant models and China-specific models

Power & Energy	Auto shut-off	Shut-off when inactive	15min / 20 min / 30 min / 1 h / 2 h / 3 h / 4 h / 8 h / 12 h / 24h / Never	20 min	—	Set idle time until automatic power OFF.	
		Shut-off when watching	15min / 20 min / 30 min / 1 h / 2 h / 3 h / 4 h / 8 h / 12 h / 24h / Never	4 h	Allowed	Set idle time until automatic power OFF even while watching videos.	
		Shut-off when no signal	On / Off	On	—	Power automatically turns OFF if there is no input signal for 5 minutes.	
		Power saving	Off / Low / High	Off	—	Set automatic brightness and operation adjustment level to reduce power consumption.	
		ECO Dashboard	—	—	—	Action : Open ECO Menu	
About	System software update	Software update	—	—	—	Action: Search to confirm the version.	
		Automatically check for update	On / Off	Off	Allowed	Enable automatic software updates. Requires an internet connection at all times.	
	Device name	—	—	—	Allowed	—	
	Reset	Factory data reset	—	—	—	Resets both main settings and Pro settings.	
	Status	—	—	—	—	Current stats.	
	Legal information	—	Third Party Source System WebView licenses Consumer Information Sony legal End user license agreement	—	—	Check legal information from the list.	
	Model	—	—	—	—	Monitor model name.	
	Android TV OS version	—	—	—	—	Display Android TV OS version.	
	Android TV OS security patch level	—	—	—	—	Display Android TV OS security patch level.	
	Kernel version	—	—	—	—	Display kernel version.	
	Android TV OS build	—	—	—	—	Display Android TV OS build.	
Date & Time	Automatic date & time	On / Off	On / Off	On	Allowed	Enable automatic date and time setting.	
	Set date	—	—	—	—	Date can be set when [Automatic date & time] is OFF.	
	Set time	—	—	—	—	Time can be set when [Automatic date & time] is OFF.	
	Set time zone	—	—	—	Allowed	Select time zone (area).	
	Use 24-hour format	On / Off	On / Off	Off	—	Enable 24-hour format.	
	Auto clock display	On / Off	On / Off	Off	—	Enable automatic clock display.	
Language	—	—	—	—	Allowed	Select GUI language.	
Keyboard	Current keyboard	—	—	—	—	Display keyboard in use.	
	Manage keyboards	—	—	—	Allowed	Enable virtual keyboard.	
Storage	Internal shared storage (expect for system area)	—	—	—	—	Display internal storage capacity. When devices such as USB memory are connected, their capacity can also be checked.	
	Free up storage	Clear cache Uninstall apps	—	—	—	—	
Developer options * This feature is hidden by default.	Enable developer options	On / Off	On / Off	Off	Allowed	Enable developer options.	
	Stay awake	On / Off	On / Off	Off	Allowed	Disable display sleep mode so the screen doesn't turn off while working.	
	Enable Bluetooth HCI snoop log	Disabled / Enabled Filtered / Enabled	Disabled / Enabled Filtered / Enabled	Enabled	—	Enable Bluetooth packet capture.	
	OEM unlocking	On / Off	On / Off	Off	—	Allow bootloader unlock.	
	Picture color mode	On / Off	On / Off	Off	Allowed	Operation: Select from list of installed apps.	
	DEBUGGING	USB debugging	On / Off	On / Off	Off	—	Enable debugging via USB connection.
		Revoke USB debugging authorizations	OK / Cancel	OK / Cancel	—	—	—
		Wireless debugging	Enable / Disable	Enable / Disable	Disable	—	Enable debugging via Wi-Fi.
		Select mock location app	—	—	—	—	Specify mock location app after app installation.
		Enable view attribute inspection	On / Off	On / Off	Off	—	Enable inspection of app UI element attribute information.
		Select debug app	—	—	—	—	Operation: Select from list of installed apps.
		Wait for debugger	On / Off	On / Off	Off	—	Enable waiting for debugger connection and actions to execute after connection.
		Verify apps over USB	On / Off	On / Off	On	—	Verify operation of apps installed via USB.
		Logger buffer sizes	Off / 64 K / 256 K / 1 M / 4 M / 8 M	Off / 64 K / 256 K / 1 M / 4 M / 8 M	256 K	—	Set size of memory area for temporarily storing logs.
		Wireless display certification	On / Off	On / Off	Off	—	Enable display of confirmation screen when there is a connection request.
	NETWORKING	Enable Wi-Fi Verbose logging	On / Off	On / Off	Off	—	Increase Wi-Fi log level to display detailed SSID (network name) and RSSI (received signal strength).
		Mobile data always active	On / Off	On / Off	Off	—	Always enable mobile data even when connected to Wi-Fi.
	INPUT	Select USB Configuration	Charging / MTP(Media Transfer Protocol) / PTP(Picture Transfer Protocol) / RNDIS(USB Ethernet) / MIDI	Charging / MTP(Media Transfer Protocol) / PTP(Picture Transfer Protocol) / RNDIS(USB Ethernet) / MIDI	—	—	Select operation mode when connected via USB.
	DRAWING	Show taps	On / Off	On / Off	Off	—	Display circles or dots at the position tapped on the touchscreen.
		Pointer location	On / Off	On / Off	Off	—	Overlay detailed touch information on the screen.
		Show surface updates	On / Off	On / Off	Off	—	Flash the entire screen each time the display area is updated.
		Show layout bounds	On / Off	On / Off	Off	—	Visualize layout information such as clip boundaries and margins.
		Force RTL layout direction	On / Off	On / Off	Off	—	Set screen layout direction to RTL for testing right-to-left language layouts.
		Window animation scale	Off / .5x / 1x / 1.5x / 2x / 5x / 10x	Off / .5x / 1x / 1.5x / 2x / 5x / 10x	1x	—	Adjust animation speed when launching/closing apps.
		Transition animation scale	Off / .5x / 1x / 1.5x / 2x / 5x / 10x	Off / .5x / 1x / 1.5x / 2x / 5x / 10x	1x	—	Adjust animation speed for screen transitions within apps.
		Animator duration scale	Off / .5x / 1x / 1.5x / 2x / 5x / 10x	Off / .5x / 1x / 1.5x / 2x / 5x / 10x	1x	—	Adjust speed for detailed UI element animations within apps.
		Simulate secondary displays	None / 480p / 480p (secure) / 720p / 720p (secure) / 1080p / 1080p (secure) / 4K / 4K (secure) / 4K (upscaled) / 4K (upscaled, secure) / 720p, 1080p (dual screen)	None / 480p / 480p (secure) / 720p / 720p (secure) / 1080p / 1080p (secure) / 4K / 4K (secure) / 4K (upscaled) / 4K (upscaled, secure) / 720p, 1080p (dual screen)	4K	—	Simulate a virtual external display on the display screen.
		HARDWARE ACCELERATED RENDERING	Show view updates	On / Off	On / Off	Off	—
	Show hardware layers updates		On / Off	On / Off	Off	—	Display UI elements using hardware layers in green when updated.
	Debug GPU overdraw		Off / Show overdraw area / Show areas for Deuteranomaly	Off / Show overdraw area / Show areas for Deuteranomaly	Off	—	Color-code areas where the same pixel is drawn multiple times.
	Debug non-rectangular clip operations		Off / Draw non-rectangular clip region in blue / Highlight tested drawing commands in green	Off / Draw non-rectangular clip region in blue / Highlight tested drawing commands in green	Off	—	Visualize clipping operations in non-rectangular regions.
	Force 4x MSAA		On / Off	On / Off	Off	—	Force enable multisampling anti-aliasing (MSAA) in OpenGL ES 2.0 apps.
	Disable HW overlays	On / Off	On / Off	Off	—	When enabled, always use GPU compositing.	

Setting (Android TV OS 14)

Settings are based on the worldwide model. Some settings may differ from EU RED-DA compliant models and China-specific models

	Simulate color space		Disabled / Monochromacy / Deuteranomaly (red-green) / Protanomaly (red-green) / Tritanomaly (blue-yellow)	Disabled	—	Simulate color vision deficiencies.
MEDIA	Disable USB audio routing		On / Off	Off	—	Disable automatic switching to USB audio devices.
AUDIO	Record audio		On / Off	Off	—	Enable immediate audio recording start during debugging.
MONITORING	Strict mode enabled		On / Off	Off	—	Flash the screen when time-consuming processing occurs on the main thread.
	Profile HWUI rendering		Off / On screen bars / In adb shell dumpsys gfxinfo	Off	—	Display rendering performance graph.
	Enable OpenGL traces		None / Logcat / Systrace (graphic) / Call stack on glGetError	None	—	Enable tracing (recording) of OpenGL API calls.
APPS	Don't keep activities		On / Off	Off	—	Immediately destroy apps when moved to background.
	Background process limit		Standard limit / No background processes / At most 1 process / At most 2 processes / At most 3 processes / At most 4 processes	Standard limit	—	Limit the number of background processes that can run simultaneously.
	Show background ANRs		On / Off	Off	—	Display notification when background apps are not responding (ANR).
	Standby apps		—	—	—	Set apps to standby mode and restrict background operation. Operation: Check status in app list, toggle enable/disable.
	Force allow apps on external		On / Off	Off	—	Enable writing to external storage for all apps regardless of manifest values.
	Force activities to be resizable		On / Off	Off	—	Resize all activities in multi-window regardless of manifest values.
System sounds			On / Off	On	Allowed	Enable operation sounds.
Parental controls	Apps		—	—	—	Set PIN. Select apps to restrict from app list.
Settings available after 4-digit PIN setup	Screen time	Restricted screen time	On / Off	Off	—	—
		Usage time limit	1 h / 2 h / 3 h / Custom	—	—	Configurable when [Device usage restrictions] is enabled.
		Restricted time slot	—	—	—	Time setting.
		Repeat	—	Everyday	—	Select by day of week.
	Change PIN	—	—	—	—	4-digit number.
LED indicator	Operational response		On / Off	On	Allowed	Select disable/enable for display operation response lamp.
Apple AirPlay & HomeKit	Apple AirPlay and HomeKit settings	AirPlay	On / Off	On	Allowed	—
		Require Code	First time only / Every time / Use password instead	First time only	Allowed	—
		Accessibility	Closed Captions & SDH Select Style	—	—	—
		About AirPlay	—	—	—	—
	Reset	Reset Paired Devices	—	—	—	—
	HomeKit Set Up	—	—	—	—	—
Initial setup			—	—	—	—
Restart			—	—	—	—

Accessibility

Text magnification			Enable / Configuration (Text color, Duration)	—	—	Settings for enlarging caption size, color settings, etc.
Color inversion			On / Off	Off	—	Enable inversion of text and background colors.
Mono audio			On / Off	Off	—	Enable mono audio output when using headphones or Bluetooth devices.
Text scaling			Small(85%) / Default(100%) / Large(115%) / Largest (130%)	Default	—	Adjust text size in settings and information menus.
Bold text			On / Off	Off	—	Display text in settings and information menus in bold.
Color correction			On / Off On : Select color mode	Off	—	Adjust screen color tone to make the screen easier to see for users with visual constraints.
Accessibility shortcut			On / Off	On	Allowed	When enabled, pressing and holding the remote control mute button for 3 seconds launches [Magnification], [Color inversion], [Mono audio], [Font size], [Bold text], [Color correction].
Keyboard accessibility	Time to take action (accessibility timeout)		Default / 10 sec / 30 sec / 1 min / 2 min	Default	—	Set accessibility timeout time.
	Key repeat delay	Delay before repeat	Default / 3 sec / 5 sec	Default	—	Set long press time for continuous input of the same key when holding down a key.
		Repeat rate	Default / Slow / Fast	Default	—	Set input speed for continuous input of the same key when holding down a key.
Audio description			On / Off	Off	—	Enable function to read aloud content descriptions.
Subtitle settings	Display		On / Off	Off	—	Enable caption display.
	Language		—	—	—	—
	Text size		Very small / Small / Normal / Large / Very large	Normal	—	Caption size setting.
High contrast text (Experimental)			On / Off	Off	—	—
Power-on Volume			On / Off	Off	—	Enable function to read aloud content descriptions.

Remotes & accessories

Bluetooth			On / Off	On	Allowed	Enable Bluetooth.
Pair accessory			—	—	—	Pair accessory devices. Possible when connected.
RS232C Control			—	—	—	Enable RS232C control.

Pro setting (Android TV OS 14)

Settings are based on the worldwide model. Some settings may differ from EU RED-DA compliant models and China-specific models

Item	Options	Default	Export via USB	Description	
Actions					
Start Pro mode			–	Action	
Initialize Pro setting			–	Action	
Current settings			–	Action	
Export Pro settings			–	Action	
Startup services			–	Action	
Install APK			–	Action	
Settings					
AC power on	Standard / Always on / Off	Standard	Allowed	Display power sync with building/room main power.	
Wake-up on signal	Enable / Disable	Disable	Allowed	Auto input switch on signal detection.	
Home key behavior	Home menu / Web app / Web app/Home menu / Android home app	Home menu	Allowed	Home button display settings.	
NTP server	–	–	Allowed	Action	
Pro mode lock	–	–	Allowed	PIN code requirement settings when switching from Pro mode to Normal mode.	
Charge USB during Standby mode / Networked standby mode	Enable / Disable	Disable	Allowed	USB charging while display is off.	
Restore picture & sound adjustments	Enable / Disable	Disable	Allowed	Restore to the saved preset settings on power cycle (OFF → ON).	
Developer options	Power state control by apps	Enable / Disable	Disable	Allowed	Allow power control function using Broadcast Intents by Android apps.
	Custom button URL	–	–	Allowed	Custom button settings for the remote control.
Wi-Fi access point	Wi-Fi access point	Enable / Disable	Disable	Allowed	–
	SSID	–	–	Allowed	–
	Security	WPA2-PSK / Open network	–	Allowed	–
	Password	–	–	Allowed	Set using 8-63 characters
Admin password	–	–	Allowed	Selected app actions	
USB drive auto run	Import settings	–	–	Allowed	Selected app actions
	Install BPK	–	–	Allowed	Selected app actions
	Launch web app	–	–	Allowed	Selected app actions
	Install web app	–	–	Allowed	Selected app actions
HTML5 platform	Root certificates	–	–	Allowed	Action
	Client certificates	–	–	Allowed	Action
	Confirm server certificates	Enable / Disable / Confirm	Enable	Allowed	Setting to enable or disable server certificate verification.
	Web permissions	–	–	Allowed	Set monitor access permissions.
	Auto recovery	On / Off	Off	Allowed	Enable automatic recovery on web app errors.
	Require PIN to launch a web app when using Pro mode lock	Don't require PIN / Require PIN	Don't require PIN	Allowed	–
	Web app orientation	Prioritize web app / Portrait / Landscape	Prioritize web app	Allowed	Set orientation: follow manifest / specify
DHCP hostname	–	–	Allowed	Host registration	
Initial source and volume					
Initial input source	Default / External input / Startup app / Android app	Default	Allowed	Set the initial screen on monitor power-on.	
Initial and maximum volume	Initial volume	0-100	Disable	Allowed	Set initial volume on monitor power-on
	Maximum volume	0-100	100	Allowed	Set maximum monitor speaker volume.
Timers	–	–	Allowed	Set auto ON/OFF time.	
Function restrictions					
Display/Remote controls	Display control	Enable / Disable	Enable	Allowed	Restrict physical button operations in Pro mode.
	IR remote control	Enable / Disable	Enable	Allowed	Restrict IR remote control operations in Pro mode.
External inputs	HDMI 1	Use with labels / Use without labels / Not use	Use with labels	Allowed	In Pro mode, viewing and modifying [External Input Settings] is restricted.
	HDMI 2	Use with labels / Use without labels / Not use	Use with labels	Allowed	In Pro mode, viewing and modifying [External Input Settings] is restricted.
	HDMI 3 (eARC/ARC)	Use with labels / Use without labels / Not use	Use with labels	Allowed	In Pro mode, viewing and modifying [External Input Settings] is restricted.
	HDMI 4	Use with labels / Use without labels / Not use	Use with labels	Allowed	In Pro mode, viewing and modifying [External Input Settings] is restricted.
Apps	Enable (appears at app menu) / Disable	Disable	Allowed	Enable or disable app usage in Pro mode.	
Input	Input	Default view / Basic view	Basic view	Allowed	
	Inputs menu customization	–	–	Allowed	
Quick Settings	Default view / Basic view / Off	Basic view	Allowed	Restrict Quick Settings menu in Pro mode.	