

EZ20L系列Android TV OS 14

设置基于全球版机型。与中国专用机型可能存在部分差异。

Pro settings

Item		Options	Default Value	Description	
ACTIONS	Initialize Pro settings			Return all Pro settings to their default values.	
	Install APK			Install the APK file to the display using a USB drive.	
SETTINGS	PC input optimization	Auto / Off	Off	Show the typical PC format in full screen by keeping the aspect ratio. true: Enables automatic optimization of the screen display. Off: Show the typical PC format in full screen by keeping the aspect ratio.	
	Wake-up on signal	Disable / Always enabled / Input change only / Specified hours	Disable	Automatically turn on the display and switch input when HDMI input is connected. Automatically turn off the display when HDMI input is disconnected. Always enabled: Enables the power control function when the HDMI input is detected and when the HDMI input is disconnected. Input change only: The unit automatically turns on and switches the input only when the HDMI input is detected. Specified hours: Specify the start/end time for this function to be enabled.	
	Lock settings	Disable / Enable	Disable	Show the typical PC format in full screen by keeping the aspect ratio. true: Enables automatic optimization of the screen display. Off: Show the typical PC format in full screen by keeping the aspect ratio.	
INITIAL SETTINGS	Initial input source	Default / External input (Video / HDMI 1 / HDMI 2 / HDMI 3 (eARC/ARC)) / Android app	Default	Set the initial input when the display is turned on. Default: Last displayed input or app is shown. External input: Specified external input is shown. Android app: Specified Android app is shown.	
	Power Scheduling	On / Off	Off	Set the times for the display to turn on and off automatically, including a schedule to run periodically (daily or weekly).	
	Periodic restart	On / Off	Off	Restart the display at a set time. This can schedule periodic restarts (daily or weekly). You can select whether a restart should be executed or not while the display is on.	
FUNCTION RESTRICTIONS	Display/Remote controls	Display control	On / Off	On	Enable or disable the buttons on the display.
		IR remote control	On / Off	On	Enable or disable the buttons on the IR remote control.
	External inputs	HDMI 1	Use with labels / Use without labels / Not use	Use without labels	External input can be restricted.
		HDMI 2	Use with labels / Use without labels / Not use	Use without labels	Use with labels: The input info label appears on the screen.
		HDMI 3 (eARC/ARC)	Use with labels / Use without labels / Not use	Use without labels	Use without labels: The input info label doesn't appear on the screen.
Video	Use with labels / Use without labels / Not use	Use without labels	Not use: External input is disabled.		

Monitor Settings

Item		Options	Default Value	Description		
Info banner		On / Off	On	Display information when input is changed.		
External inputs	Manage inputs	HDMI 1	Show / Hide	Show	Show/hide and label inputs information.	
		HDMI 2	Show / Hide	Show	Display settings for HDMI 1 input.	
		HDMI 3 (eARC/ARC)	Show / Hide	Show	Display settings for HDMI 2 input.	
		Video	Show / Hide	Show	Display settings for HDMI 3 (eARC/ARC) input.	
		Video	Show / Hide	Show	Display settings for AV input.	
	HDMI CEC Settings	CEC	On / Off	On	—	
		Device auto power off	On / Off	On	—	
		TV auto power on	On / Off	On	—	
	HDMI signal format	HDMI 1	Standard format / Enhanced format	Standard format	Standard: Optimizes compatibility with connected devices.	
		HDMI 2	Standard format / Enhanced format	Standard format	Enhanced: Prioritizes image quality for 4K devices.	
HDMI 3 (eARC/ARC)		Standard format / Enhanced format (ALLM)	Standard format	Enhanced format (ALLM): Displays images from 4K supported devices with priority on image quality. Supports Auto Low Latency Mode (ALLM) when connecting to game.		
Advanced settings	RS232C control	On / Off	Off	Control function for professional use. If you change this setting, the TV will restart automatically.		
Display & Sound	Picture adjustments	Picture mode	Vivid / Standard / Cinema / Game / Graphics / Photo / Custom	Standard	Picture quality presets according to usage.	
		Auto picture mode	On / Off	On	—	
		Brightness	—	—	—	
		Colour	—	—	Adjust the color saturation level.	
		Advanced	Brightness	—	—	—
			Color	—	—	—
			Clarity	—	—	—
			Motion	—	—	—
			Video options	—	—	—
		Reset	—	—	—	
	Screen	Wide mode	Auto / Wide zoom / Normal / Full / Full pixel / Zoom / 14:9	Auto	Adjust the picture size.	
		*Settings for each input	Wide zoom / Normal	Wide zoom	Switches to the appropriate aspect ratio.	
	Sound	Dialogue enhancer	Min~Max (0~6)	Min	Adjusts so that human voices can be heard clearly.	
			Surround	On / Off	Off	Virtually reproduces 5.1ch surround audio content with immersive sound.
		*Settings for each input	Equalizer	Min~Max (-12~12) Frequency: 125Hz, 250Hz, 500Hz, 1kHz, 2kHz, 4kHz, 8kHz	All 0	Adjusts sound quality for each frequency band.
			TV position	Table-Top Stand / Wall Mount	Table-Top Stand	Select monitor position.
			Common > Balance	L15-R15	0	Adjust overall audio output direction.
		Advanced	Common > Digital audio out volume	Min~Max (0~100)	Max	Adjust when you notice volume differences when switching between broadcasts or inputs.
			Input related > Volume offset	Min~Max (-6~6)	0	Compensates for volume level differences between input signals. (Only for Dolby Digital audio)
			Input related > Dynamic range	Standard / Compress	Standard	Resets sound quality settings to factory default.
Reset	—	—	—			
Audio output	Speakers	Built-in speakers / Audio system	Built-in speakers	Audio output destination settings.		
	Digital audio out	Auto / PCM / Pass through mode	—	Select the audio format for the audio system connected with HDMI or optical digital cable. Available when [Speakers] is set to [Audio system].		
Text scaling	Small / Default / Large / Largest	—	—	—		
Network & Internet	Wi-Fi	On / Off	Off	Enable Wi-Fi.		
	Available networks	Available network list	—	Check the list of available networks.		
	Other Options	Quick connect	—	—	Quick connect helps you to quickly connect to your Wi-Fi by scanning QR code on your phone.	
		Add new network	—	—	—	
		Scanning always available	On / Off	—	Let Google's location service and other apps scan for networks, even when Wi-Fi is off.	
	Ethernet	Not connected/connected	—	—	—	
		Proxy settings	—	—	—	
		IP settings	—	—	—	
		Network status	—	—	—	
	Related functions	Remote start	Off / On (Networked standby) / On (Powered on by apps)	Off	Allows an external device to turn on the TV.	
IP control		Control remotely	On / Off	Off	Let registered remote device control this TV. This may consume more energy.	
		Authentication	None / Pre-Shared Key	Pre-Shared Key	Authentication method settings.	
Pre-Shared Key	Text entry	—	—	Pre-Shared Key settings.		
Simple IP control	On / Off	Off	—	Enable Simple IP control.		
Accounts & Profiles	Add account	—	—	Sign in to get new apps, recommendations, movies and more from Google.		
Privacy	DEVICE SETTINGS	Location	Location status	Use Wi-Fi to estimate location / Off	Use Wi-Fi to estimate location	Check Google location services status.
			Scanning always available	On / Off	On	Set whether to always scan for location.
		RECENT LOCATION REQUESTS	—	—	—	
		Microphone	Microphone access	true / false	true	—
	Recently accessed by		—	—	—	
	Camera	App access to microphone	—	—	—	
		Camera access	true / false	true	—	
	Recently accessed by	—	—	—		
	App access to camera	—	—	—		
	Usage & diagnostics	On / Off	On	—	Allow usage access.	
Ads	Reset advertising ID	—	—	Reset advertising ID.		

APP SETTINGS	App permissions						
	Special app access	Energy optimization	Select permitted apps from the list.		Optimize energy use of apps		
		Usage access	Usage access	Select permitted apps from the list.		Usage access allows an app to track what other apps you're using and how often, as well as your carrier, language settings, and other details.	
			Notification access	Select permitted apps from the list.		These apps will be able to read all notifications, including personal information such as contact names and the text of messages you receive. They will also be able to dismiss notifications or trigger action buttons they contain.	
			All files access	Select permitted apps from the list.		Allow this app to read, modify and delete all files on this device or any connected storage volumes. If granted, app may access files without your explicit knowledge.	
			Display over other apps	Select permitted apps from the list.		Allow an app to display on top of other apps you're using. It may interfere with your use of those apps or change the way they seem to appear or behave.	
			Modify system settings	Select permitted apps from the list.		This permission allows an app to modify system settings.	
			Alarms & reminders	Select permitted apps from the list.		Allow apps to set alarms and schedule time-sensitive actions. This lets the apps run in the background, which may use more power. If this permission is off, existing alarms and time-based events scheduled by the app won't work.	
		Turn screen on	Select permitted apps from the list.		Allow an app to turn the screen on. If granted, the app may turn on the screen at any time without your explicit intent.		
	Ads, Manage your ads settings, such as resetting your advertising ID.	Unknown sources			Allow installation of apps from sources other than the Play Store		
	Create restricted profile						
Apps	Same settings as App permissions, Special app access, and See all apps in Privacy. Can also be configured from here.						
System	Accessibility	Captions			Enable subtitles.		
		High contrast text (Experimental)	On / Off	Off			
		Text to speech	Speech Recognition and Synthesis from Google			Enable Google Voice Service.	
			Engine configuration			Detailed settings for text-to-speech method.	
			Speech rate	60% / 80% / 100% / 150% / 200% / 250% / 300% / 350% / 400%	100%		Set text-to-speech speed.
			Listen to an example			Play sample.	
			Default language status			Display default.	
		Accessibility shortcut	Enable accessibility shortcut	On / Off	On	Enable voice readout (limited function version).	
			Shortcut service	TalkBack / Switch Access / Text magnification / Screen reader (limited support)		Select for Shortcut service.	
		Talk Back	Enable	On / Off	Off	Enable TalkBack.	
			Configuration			Detailed settings for TalkBack.	
		Switch Access	Enable	On / Off	Off	Enable Switch Access.	
			Configuration			Detailed settings for Switch Access.	
		Text Magnification	Enable	On / Off	Off	Enable text magnification.	
			Configuration	Color Duration		Detailed settings for text display.	
	Screen reader (limited support)	Enable	On / Off	Off	Enable voice readout.		
		Configuration			Detailed settings for voice readout.		
	Text scaling		Small / Default / Large / Largest		Scale: 85% < 100% < 115% < 130%		
	Bold text		On / Off	Off			
	Color correction						
	About	System update			This TV will send a unique number to Sony Corporation to provide software updates.		
		Device name					
		Reset	Factory reset	Erase everything / Cancel			
		Status		IP address Device MAC address Bluetooth address Serial number Uptime	Check current status.		
		Legal information	Third Party Source				
			Google legal				
			Sony legal				
			End user license agreement				
			System WebView licenses				
		Consumer Information					
		Model					
		Android TV OS version					
		Android TV OS security patch level					
		Kernel version					
		Android TV OS build					
	Model name						
	Date & time	Automatic date & time	Use network-provided time / Off	Use network-provided time	Enable automatic date and time setting.		
		Set date					
		Set time					
		Set time zone	Select time zone (area)		Select time zone (area).		
		Use 24-hour format	On / Off	On	Enable 24-hour format.		
	Power and Energy	Auto clock display	On (always) / On (every hour) / Off	Off	Enable automatic clock display.		
		Power saving	Off / Low / High	Off			
		Idle display power off	Off / 1h / 2h / 4h / 24h	4h	Automatically turns off the TV after a set period of inactivity.		
	Auto shut-off	On / Off	On	No input signal detected. The display will turn off in 5 minutes.			
	Language	Keyboard	Current keyboard	Select language			
		Gboard Settings	Current version				
			Langauges				
			Terms of Service			Display the terms of service (webpage).	
			Privacy Policy			Display the privacy policy (webpage).	
			Open source licences			Licence details for open-source software	
			Share usage statistic			Automatically send keyboard usage statistics to Google	
		Manage keyboards					
	Storage	DEVICE STORAGE	Internal shared storage	Display internal storage capacity			
		Free up storage		Clear cache / Uninstall apps			
		Customize channels		Play Next / Home screen channels	Enable "Next recommendations" display.		
		Enable video previews					
	Home screen	Apps	Reorder apps		Select an app, press [OK], move it with the directional buttons, and press [OK] to place.		
			Reorder games		Select an app, press [OK], move it with the directional buttons, and press [OK] to place.		
		Open source licences	Android TV Home				
	Android TV Core Services		Display license				
	Screen saver	Screen saver	Turn screen off / Backdrop / Colors	Backdrop			
		When to start	5 minutes / 15 minutes / 30 minutes / 1 hour / 2 hours	15 minutes			
		Start now					
	Google Cast	Let other control your cast media	Always / While casting / Never	While casting	Show a notification on all Android devices connected to your Wi-Fi and let them control media casting to this device.		
	System sounds		On / Off	On			
	Parental controls	Parental controls	true / false	false			
		External input block	Block all / HDMI 1 / HDMI 2 / HDMI 3(eARC/ARC) / Video				
		Change PIN					
	Restart						
	Apple AirPlay and HomeKit	AirPlay		On / Off	On		
		Require Code	Require Code	First Time Only / Every Time / Use Password Instead	First Time Only		
			Reset			Reset paired devices	
		Subtitles and Captioning	Closed Captions and SDH				
			TEXT > Font > Font	San Francisco / Helvetica / Cinecav X / Menlo / Lucida Grande / Avenir / COPPERPLATE / Savove	San Francisco		
			TEXT > Font > Video Override	On / Off	On		
			TEXT > Size > Size	Small / Medium / Large / Extra Large	Medium		
			TEXT > Size > Video Override	On / Off	On		
			TEXT > Font Colour > Font Colour	White / Cyan / Blue / Green / Yellow / Magenta / Red / Black	White		
			TEXT > Font Colour > Video Override	On / Off	On		
			BACKGROUND > Background Colour > Background Colour	White / Cyan / Blue / Green / Yellow / Magenta / Red / Black	Black		
			BACKGROUND > Background Colour > Video Override	On / Off	On		
			BACKGROUND > Opacity > Opacity	50% / 100% / 75% / 25% / 0%	50%		
			BACKGROUND > Opacity > Video Override	On / Off	On		
			ADVANCED > Text Opacity > Text Opacity	Opaque / Semi-Transparent / Transparent	On		
	ADVANCED > Text Opacity > Video Override		On / Off	On			
	ADVANCED > Text Edge Style > Text Edge Style	None / default value / Drop Shadow / Raised / Depressed / Uniform	None				

		ADVANCED > Text Edge Style > Video Override	On / Off	On	—
		ADVANCED > Text Highlight > Text Highlight	Black / White / Blue / Red / Green / Cyan / Yellow / Magenta	Black	—
		ADVANCED > Text Highlight > OPACITY	0% / 25% / 50% / 75% / 100%	0%	—
		ADVANCED > Text Highlight > Video Override	On / Off	On	—
	About AirPlay	About AirPlay > AirPlay Logging	—	—	—
		About AirPlay > Analytics	—	—	—
		About AirPlay > Acknowledgements	—	—	—
		Versions>AirPlay Version	—	—	—
		Versions>App Version	—	—	—
		Versions>App Engine	—	—	—
		Versions>Streaming Engine	—	—	—
	Reset		—	—	—
	Set Up	HomeKit	—	—	Easily and securely control this TV using the Home app, Siri, or from Control Centre on your Apple devices.
Remotes & Accessories	Bluetooth		On / Off	On	—
	Add accessory		—	—	—
	Remote control		{Bluetooth devices} / Add devices	—	—
Help & Feedback	Help		—	—	—

EZ20L系列Android TV OS 11

设置基于全球版机型。与中国专用机型可能存在部分差异。

Pro settings

Item		Options	Default Value	Description	
ACTIONS	Initialize Pro settings			Return all Pro settings to their default values.	
	Install APK			Install the APK file to the display using a USB drive.	
SETTINGS	PC input optimization	true / Off	Off	Show the typical PC format in full screen by keeping the aspect ratio. true: Enables automatic optimization of the screen display. Off: Show the typical PC format in full screen by keeping the aspect ratio.	
	Wake-up on signal	Disable / Always enabled / Input change only / Specified hours	Disable	Automatically turn on the display and switch input when HDMI input is connected. Automatically turn off the display when HDMI input is disconnected. Always enabled: Enables the power control function when the HDMI input is detected and when the HDMI input is disconnected. Input change only: The unit automatically turns on and switches the input only when the HDMI input is detected. Specified hours: Specify the start/end time for this function to be enabled.	
	Lock settings	true / Off	Disable	Show the typical PC format in full screen by keeping the aspect ratio. true: Enables automatic optimization of the screen display. Off: Show the typical PC format in full screen by keeping the aspect ratio.	
INITIAL SETTINGS	Initial input source	Default / External input (Video / HDMI 1 / HDMI 2 / HDMI 3 (eARC/ARC)) / Android app	Default	Set the initial input when the display is turned on. Default: Last displayed input or app is shown. External input: Specified external input is shown. Android app: Specified Android app is shown.	
	Power Scheduling	true / Off	Off	Set the times for the display to turn on and off automatically, including a schedule to run periodically (daily or weekly).	
	Periodic restart	true / Off	Off	Restart the display at a set time. This can schedule periodic restarts (daily or weekly). You can select whether a restart should be executed or not while the display is on.	
FUNCTION RESTRICTIONS	Display/Remote controls	Display control	On / false	On	Enable or disable the buttons on the display.
		IR remote control	On / false	On	Enable or disable the buttons on the IR remote control.
	External inputs	HDMI 1	Use with labels / Use without labels / Not use	Use without labels	External input can be restricted.
		HDMI 2	Use with labels / Use without labels / Not use	Use without labels	Use with labels: The input info label appears on the screen.
		HDMI 3 (eARC/ARC)	Use with labels / Use without labels / Not use	Use without labels	Use without labels: The input info label doesn't appear on the screen.
Video	Use with labels / Use without labels / Not use	Use without labels	Not use: External input is disabled.		

Monitor Settings

Item		Options	Default Value	Description	
Info banner		On / Off	On	Display information when input is changed.	
External inputs	Manage inputs	HDMI 1	On / Off	On	Show/hide and label inputs information.
		HDMI 2	On / Off	On	Display settings for HDMI 1 input.
	[HDMI 1 - AV]: You can show or hide each input. When "Show this input" is	HDMI 3 (eARC/ARC)	On / Off	On	Display settings for HDMI 2 input.
	HDMI CEC Settings	AV	On / Off	On	Display settings for HDMI 3 (eARC/ARC) input.
		CEC	On / Off	On	Display settings for AV input.
		Auto TV off	On / Off	On	—
		Auto TV on	On / Off	On	—
	HDMI signal format	HDMI 1	Standard format / Enhanced format	Standard format	Switch the supported signal format for HDMI 1 input.
		HDMI 2	Standard format / Enhanced format	Standard format	Switch the supported signal format for HDMI 2 input.
		HDMI 3 (eARC/ARC)	Standard format / Enhanced format / Enhanced format (Dolby Vision) / Enhanced format (VRR)	Standard format	Switch the supported signal format for HDMI 3 (eARC/ARC) input.

Display & Sound *Settings for each input	Basic	Picture mode		Vivid / Standard / Cinema / Game / Graphics / Photo / Custom	Standard	Picture quality presets according to usage.	
		Auto picture mode		On / Off	On	Automatically switches picture mode according to the content of HDMI-connected devices.	
		Light Sensor		Min~Max (0~50)	40	Automatically adjusts screen brightness according to the surrounding brightness.	
	Brightness	Brightness		Min~Max (0~100)	50	Adjusts panel brightness.	
	Colour	Colour				Adjust color intensity.	
	Clarity	Sharpness		Min~Max (0~100)	50	Enhances edges and details.	
		Reality Creation	Reality Creation	Auto / Manual / Off	Manual	Improves clarity through super resolution processing and noise reduction.	
			Resolution	Resolution: Min~Max (0~100)	Resolution: 65		
		Random noise reduction		Auto / High / Medium / Low / Off	Auto	Reduces dot noise and color noise in dark areas.	
		Digital noise reduction		Auto / High / Medium / Low / Off	Auto	Reduces compression noise and other artifacts.	
	Motion	Motionflow	Motionflow	Auto / Custom / Off	Auto	Automatically enhance or weaken Smoothness for certain images.	
			Smoothness	Min~Max (0~3)	2	Adjusts the strength of smoothness by using frame interpolation on the input video.	
			Clearness	Min~Max (0~3)	1	Adjusts the strength of clarity by inserting a black frame to reduce motion blur.	
		CineMotion		High / Low / Off	Auto	Optimal conversion processing for film content.	
	Video signal	HDR mode		Auto / HDR10 / HLG / Off	Auto	Sets the HDR format of the input signal.	
		HDMI video range		Auto / Full / Limited	Auto	Sets the HDMI video range.	
		Color space		Auto / sRGB/BT.709 / DCI / BT.2020	Auto	Sets the color space.	
	Adv. color adjustment	Adv. colour temperature: Basic		RGB-Gain -40~0 RGB-Bias -20~20 Reset	RGB-Gain: MAX RGB-Bias: 0	Sets color temperature for each RGB.	
		Adv. color temperature: Multi point (10p)		Colour gamma adjustment points 1~10 RGB-Offset -20~20 Reset	Colour gamma: 1 RGB-Offset: 0	Sets color temperature for each RGB.	
	Advanced	Brightness		Min~Max (0~50)	40	Adjusts panel brightness.	
		Contrast		Min~Max (0~100)	90	Adjusts brightness and darkness by changing the signal range.	
		Gamma		Min~Max (-3~3)	-2	Adjusts the brightness balance of mid-tones.	
		Black level		Min~Max (0~100)	50	Adjusts brightness of dark areas.	
		Black adjust		High / Medium / Low / Off	Off	Emphasizes black and automatically adjusts brightness of dark areas.	
		Auto contrast adjustment		High / Medium / Low / Off	Off	Automatically corrects contrast.	
		Local dimming		High / Medium / Low / Off	Medium	Automatically corrects contrast.	
	Screen	X-tended Dynamic Range		High / Medium / Low / Off	Off	Automatically corrects contrast.	
		Wide mode		Auto / Wide zoom / Normal / Full / Zoom	Auto	Adjust the picture size.	
		4:3 default		Wide zoom / Normal	Wide zoom	Switches to the appropriate aspect ratio.	
	Sound	Input-specific	Dialogue enhancer		Min~Max (0~6)	Min	Adjusts so that human voices can be heard clearly.
			Sound customisation > Surround		Auto / On / Off	Auto	Virtually reproduces 5.1ch surround audio content with immersive sound.
			Equalizer		Min~Max (-12~12) Frequency: 125Hz, 250Hz, 500Hz, 1kHz, 2kHz, 4kHz, 8kHz	All 0	Adjusts sound quality for each frequency band.
			TV position		Table-Top / Stand	Table-Top	Select monitor position.
		Advanced	Common > Balance		L15-R15	0	Adjust overall audio output direction.
			Common > Digital audio out volume		Min~Max (0~100)	Max	—
			Input related > Volume level		Min~Max (-6~6)	0	Adjust when you notice volume differences when switching between broadcasts or inputs.
			Input related > Dynamic Range		Standard / Compress	Standard	Compensates for volume level differences between input signals. (Only for Dolby Digital audio)
			Reset		—	—	Resets sound quality settings to factory default.
	Audio output	Speakers		Built-in speakers / Audio system	Built-in speakers	Audio output destination settings.	
Audio system prioritization		On / Off	Off	When set to [On], automatically switches audio output to BRAVIA Sync compatible audio system when the monitor starts up.			
Home theater control		On / Off	—	Configure sound quality settings for the connected audio system.			
A/V sync		Auto / On / Off	Auto	Available when an audio system is connected.			
eARC mode		Auto / Off	Off	[Auto] outputs audio when an eARC compatible device is connected to HDMI 3 (eARC/ARC) terminal.			
Digital audio out		Auto 1 / Auto 2 / PCM	PCM	Sets the audio format output to an audio system connected via HDMI cable or optical digital cable.			

		Digital audio out volume	Min~Max (0~100)	Max				
		Dolby Digital Plus output	Dolby Digital Plus / Dolby Digital	Dolby Digital Plus	When using an audio system that supports ARC and Dolby Digital Plus, sets the Dolby Digital Plus output format.			
		Pass through mode	Auto / Off	Off	Outputs audio signal to the audio system without decoding.			
Network & Internet	Wi-Fi		On / Off	Off	Enable Wi-Fi.			
	AVAILABLE NETWORKS		Available network list	—	Check the list of available networks.			
	Add new network		—	—	Manually add a network.			
	Scanning always available		On / Off	On	Scan for networks using Google location services and other apps even when Wi-Fi is OFF.			
	Not connected		—	—	—			
	Proxy settings		—	—	—			
	IP settings		—	—	—			
	Network status		—	—	—			
	Related functions	Remote start	Off / On (Networked standby) / On (Powered on by apps)	Off	Allows an external device to turn on the TV.			
	IP control	Authentication	Normal / Normal and Pre-Shared Key	Normal	Authentication method settings.			
Pre-Shared Key		Text entry	—	Pre-Shared Key settings.				
Simple IP control		On / Off	Off	Enable Simple IP control.				
Control4®		On / Off	Off	Enable Control4®.				
Accounts & Profiles	sign-in	—	—	Sign in to get new apps, recommendations, movies and more from Google.				
Privacy	Location		Location status	Use Wi-Fi to estimate location / Off	Off	Check Google location services status.		
			Scanning always available	On / Off	Off	Set whether to always scan for location.		
			RECENT LOCATION REQUESTS	—	—	—		
			Usage & diagnostics	On / Off	On	Allow usage access.		
			Ads	—	—	Reset advertising ID.		
	App	App permissions		Select permitted apps from the list.	—	Optimizes power consumption of the specified app.		
		Special app access	Energy optimization	Select permitted apps from the list.	—	—	The specified app will be able to track information such as usage status and frequency of other apps, mobile carrier, language settings, etc.	
			Usage access	Select permitted apps from the list.	—	—	The specified app will be able to read all notifications. Notifications may include personal information such as contact names and the content of received messages.	
			Notification access	Select permitted apps from the list.	—	—	Select permitted apps from the list.	
			Display over other apps	Select permitted apps from the list.	—	—	Settings to allow the specified app to modify system settings.	
			Modify system settings	Select permitted apps from the list.	—	—	Select permitted apps from the list.	
		Turn screen on	Select permitted apps from the list.	—	—	Select permitted apps from the list.		
	Security & Restrictions	Unknown sources	Allow installation from unknown apps list.	—	—	Allow installation of apps from sources other than the Play Store.		
	Apps Same settings as App permissions, Special app access, and See all apps in Privacy. Can also be configured from here.							
System	Accessibility		Subtitle settings	—	—	Enable subtitles.		
			High contrast text (Experimental)	On / Off	Off	—		
	Text to speech	Speech Services by Google		On	On	Enable Google Voice Service.		
		Engine configuration		—	—	Detailed settings for text-to-speech method.		
		Speech rate		Very slow / Slow / Normal / Fast / Faster / Very fast / Rapid / Very rapid / Fastest	Normal	—	Set text-to-speech speed.	
		Listen to an example		—	—	—	Play sample.	
		Default language status		—	—	—	Display default.	
	Accessibility shortcut	Enable accessibility shortcut		On / Off	On	Enable voice readout (limited function version).		
		Shortcut service		TalkBack / Switch Access / Text magnification / Screen reader	—	—	Select for Shortcut service.	
	Talk Back	Enable		On / Off	Off	Enable TalkBack.		
		Configuration		—	—	Detailed settings for TalkBack.		
	Switch Access	Enable		On / Off	Off	Enable Switch Access.		
		Configuration		—	—	Detailed settings for Switch Access.		
	Text magnification	Enable		On / Off	Off	Enable text magnification.		
		Configuration		Color Duration	—	—	Detailed settings for text display.	
	Screen reader (limited support)	Enable		On / Off	Off	Enable voice readout		
		Configuration		—	—	Detailed settings for voice readout		
	System software update	Software update		Search and update the version	—	—	Check the monitor's software version & update.	
		Automatically check for update		On / Off	Off	—	Enable automatic software update.	
	Device name	Factory data reset		—	—	—		
	Reset	Factory data reset		Erase everything / Cancel	—	—		
	Status			IP address MAC address Bluetooth address Serial number Uptime	—	—	Check current status.	
	Legal information	Open-source licences		—	—	—	—	
		Google legal		—	—	—	—	
		Sony legal		—	—	—	—	
		Notices and licences		—	—	—	—	
		System WebView licences		—	—	—	—	
		Wallpaper		—	—	—	—	
	Model			—	—	—		
	Android TV OS version			—	—	—		
	Android TV OS security patch level			—	—	—		
	Kernel version			—	—	—		
	Android TV OS build			—	—	—		
	Date & time	Automatic date & time		On / Off	On	—	Enable automatic date and time setting.	
		Set date		—	—	—	—	
		Set time		—	—	—	—	
		Set time zone		Select time zone (area)	—	—	Select time zone (area).	
	Use 24-hour format		On / Off	On	—	Enable 24-hour format.		
	Auto clock display		On (always) / On (every hour) / Off	Off	—	Enable automatic clock display.		
	Language			Select language	—	—	Select GUI language.	
	Keyboard	Current version		—	—	—	—	
		Gboard settings	Langauges	—	—	—	—	
			Terms of Service	—	—	—	—	Display the terms of service (webpage).
			Privacy Policy	—	—	—	—	Display the privacy policy (webpage).
			Open-source licences	—	—	—	—	Licence details for open-source software
			Share usage statistic	—	—	—	—	Automatically send keyboard usage statistics to Google
	Manage keyboards		—	—	—	—		
	Storage	Storage		Internal shared storage (except for system area)	Display internal storage capacity	—	Display internal storage capacity. When devices such as USB drives are connected, their capacity can also be checked.	
						—	Enable "Next recommendations" display.	
	Home screen	Channels	Customize channels	Play Next / Home screen channels	On	—	—	
Enable video previews			On / Off	On	—	—		
Enable audio previews			On / Off	On	—	—		
Apps		Reorder apps	—	—	—	Select an app and press [OK], then use the directional buttons to move the selected app's position, and press [OK] again to place it in the specified location.		
		Reorder games	—	—	—	Select an app and press [OK], then use the directional buttons to move the selected app's position, and press [OK] again to place it in the specified location.		
Open-source licences	Android TV Home	—	—	—	—			
Screen saver	Screen saver		Sleep / Backdrop / Colors	Backdrop	—	—		
	When to start		5 minutes / 10 minutes / 15 minutes / 30 minutes / 1 hour / 2 hours	15 minutes	—	—		
	Start now		—	—	—	—		
Power & Energy	Power saving		Off / Low / High	Off	—	—		
	Idle TV standby		Off / 1h / 2h / 4h / 24h	4h	—	—		
	Auto shut-off		On / Off	On	—	—		
Cast	Let other control your cast media		Always / While casting / Never	While casting	—	—		
Restart			—	—	—	—		
Sound	System sounds		On / Off	On	—	—		
Apple AirPlay & HomeKit	AirPlay		On / Off	On	—	—		
Require Code	Require Code		First Time Only / Every Time / Use Password Instead	First Time Only	—	—		
	Reset		—	—	—	Reset paired devices		
	Subtitles and Captioning	Closed Captions and SHD		Closed Captions and SDH Font Size Font Color Background Color Opacity Text Opacity Text Edge Style Text Highlight	—	—	—	
				San Francisco / Helvetica / Cinecav X / Menlo / Lucida Grande / Avenir / COPPERPLATE / Savoye	San Francisco	—	—	
		TEXT > Font > Font		On / Off	On	—	—	
		TEXT > Font > Video Override		Small / Medium / Large / Extra Large	Medium	—	—	
		TEXT > Size > Size		On / Off	On	—	—	
		TEXT > Size > Video Override		White / Cyan / Blue / Green / Yellow / Magenta / Red / Black	White	—	—	
		Font Colour > Font Colour		On / Off	On	—	—	
		Font Colour > Video Override		50% / 100% / 75% / 25% / 0%	50%	—	—	
		Opacity > Opacity		On / Off	On	—	—	
Opacity > Video Override		—	—	—	—			

		Text Edge Style > Text Edge Style	None / default value / Drop Shadow / Raised [Z] Depressed / Uniform	None	—
		Text Edge Style > Video Override	On / Off	On	—
		Text Highlight > Text Highlight	Black / White / Blue / Red / Green / Cyan / Yellow / Magenta	Black	—
		Text Highlight > Video Override	On / Off	On	—
		OPACITY > OPACITY	0% / 25% / 50% / 75% / 100%	0%	—
		OPACITY > Video Override	On / Off	On	—
	About AirPlay	AirPlay Version	—	—	—
		AirPlay Logging	—	—	—
		Analytics	—	—	—
		Acknowledgements	—	—	—
	Set Up HomeKit		—	—	Easily and securely control this TV using the Home app, Siri, or from Control Centre on your Apple devices.
	Parental controls	External input lock	HDMI1 / HDMI2 / HDMI3(eARC/ARC) / HDMI4 / AV	Off	—
		Change PIN	—	—	—
Remotes & Accessories	Bluetooth		On / Off	On	—
	Registered devices		{Bluetooth devices} / AV d devices	—	—